

P30 CD/ MP3 Player

- CD/CD-R/CD-RW music, Mp3 file playback
- Seamless loop function / reloop function
- Loop out point real-time adjustment
- Multifunctional jog wheel for search, pitch bend and effects adjustment
- 4 independent hot cues/loops banks
- Key Lock, Fader Start, Cue Play, Relay Play functions
- Build-in Digital Effects: ECHO, FLANGER, FILTER, BREAK
- Reliable Anti-Shock playback with buffer memory



Specification

Power: AC 115/230V, 50/60Hz, 14.5W
 Weight: 3.08 Kg
 Size: 223 (W) x 296.7 (D) x 105.9 (H)mm
 Media: CD, CD-R, CD-RW(CD music and MP3 format)
 Channel balance: Nominal within, Limit 0.5dB within 1dB @1KHz,0dB
 Frequency response: Nominal +/-0.2dB, Limit +/-1dB @ 20Hz-20KHz,0dB output
 THD + N: Nominal 0.005%, Limit 0.01% @ 1KHz,0dB
 S/N ratio: Nominal 120dB, Limit 90dB @ 1KHz,0dB
 Output: RCA output, Digital Out, Headphone Out



Features

1. CD/CD-R/CD-RW music, Mp3 file playback



The P30 can read, display, and play MP3 files written to CD-Rs, providing DJs with the ability to store music on a single media or for extended playback time. Files can be searched for easily either manually or by scanning or using file search functions including File search and File/Folder search. Additionally MP3 ID3 information tags can be viewed on the display.

2. 4-Pad Memory Points Triggers

Every CD/MP3 can be saved 4 memo points for Hot Cues and Loops. With 2000 memo points on-board, the P30 can store your Hot Cues and Loops on any audio CD/MP3 track and recall them at a later time when that track is cued in CD drive.

3. 4 Digital Sound Effects

The P30 provides four digital sound effects, including ECHO, FLANGER, FILTER and BREAK, to enhance creativity and performance. Moreover, effect parameters Time and Depth can be adjusted independently via the jog wheel.

4. Seamless Loop and ReLoop

With this function, any section on music can be played repeatedly between in & out points with no break in sound or limit in length. Once the loop is set, it can then be looped continuously or until the ReLoop/Exit button is pressed. The loop can be re-triggered at any time by hitting the ReLoop/Exit button again.

5. Key Lock

The Key Lock function locks the pitch of the track even when you adjust the speed of the track. You can speed up or slow down the beat without any noticeable difference in vocal and music pitch.

6. Multi-functional Touch Sensitive Jog Wheel

The high resolution, touch-sensitive Jog Wheel can accurately reproduce hand scratching effects of vinyl records. The Jog Wheel can also perform other vital functions such as pitch bending, scanning, frame searching, parameter control for effects, and pitch/volume control for sampling.

7. Fader Start Play

Linked with a compatible mixer, the Fader Start Play function makes the mixer's fader perform back cue and quick start functions.



8. Anti-Shock Buffer Memory

Anti-Shock

Sound jumps or skipping is prevented by using Anti-Shock buffer memory for continuous playback even in the event of a bump or knock.



Other Functions

- Instant start via 1 bit technology (8 fold)
- Auto Cue
- ReLoop
- Seamless Loop
- Track and folder searching system
- Onboard file and folder browsing
- Large extra bright display
- Pitch range $\pm 4\%$, $\pm 8\%$, $\pm 16\%$ and $\pm 100\%$
- Tempo lock
- Auto BPM & Tap
- Digital S/PDIF & Analog RCA outputs
- Single and Continuous play modes

*All specifications and appearances are subject to change without notice. VOXOA reserves the rights to change the design for products improvement.

VOXOA Co., LTD

Suite 1801-5,18/F., Tower 2, China Hong Kong City,
 33 Canton Road, Tsim Sha Tsui, Kowloon, Hong Kong
 http://www.voxoa-pro.com
 Email: service@voxoa-pro.com

