

S60 Digital Media DJ Work Station

- Digital DJ Workstation: USB player + 2-ch Mixer + Midi Controller
- 2 USB sockets for external USB device support
- All 94 control elements are MIDI compatible (Mac/PC)
- 4 Hot Cues/Loops
- Fader Start, Relay Play, Key Lock functions
- 4 digital sound effect: Echo, Flanger, Filter, Skid
- High quality 100 mm long pitch fader ($\pm 6\%$, $\pm 10\%$, $\pm 16\%$ and $\pm 100\%$)
- VOXOA TUNEBOX software makes reading and searching files quicker and easier.
- 2-ch Mixer with Three-band EQ & kill features for each band
- Input: Line x 2 (RCA), Phono x 2 (RCA), MIC x 2 (XLR/1/4 Inch Combo x 1, 6.3mm x1) + USB x2
- Output: Balanced (XLR) x 1, Unbalanced (RCA) x1, Unbalanced Booth (RCA) x1, USB MIDI x 1
- 2 MIC with level control, tone adjust and talkover
- Replaceable Crossfader with 3 curve switch
- Booth out with level adjust



Specification

Power: AC100-240V, 50/60Hz, 14 W
 Weight: 3.5 kg
 Size: 420 (W) x 300 (D) x 90~75(H)mm
 Frequency Response: LINE: 20~20k Hz ; PHONO: 20~20kHz ;
 MIC: 20 - 20K Hz
 S/N Ratio: LINE,: >73dB ; PHONO: > 73dB ; MIC: > 63dB
 THD + N: LINE/AUX: <0.06% ; PHONO: <0.07% ; MIC: <0.07%
 Input: Line x 4 (RCA), Aux/Phono x 4 (RCA), Microphone x 2
 (XLR/1/4 Inch x 1, 6.3mm x1), USB x 2
 Output: Balanced Output (XLR) x1, Unbalanced Output(RCA) x1,
 Booth (RCA) x1, USB MIDI x 1



Features

1. All-in-one Design

The S60 Digital DJ Workstation is a dual USB player and a high performance mixer in an elegant all-in-one design. Set up of the S60 is easy and fast because you don't need to waste time connecting cables. You just need to bring the S60 and USB storage device. It's perfect for DJs who work events, for clubs that need to be able to dismantle their system quickly, and for any other DJ on the move. Moreover, the S60 is also a MIDI controller that can fully control any DJ software. The comprehensive MIDI compatibility all 94 control elements can be applied as a MIDI control device.



2. Memo Points with 4 Trigger Pads

4 memo points can be saved per track for Hot Cues and Loops. The S60 can store your Hot Cues and Loops on any audio track and recall them later when that track is cued in the CD drive. The number of memo points is limited only by your USB memory capacity. This memo function can be used like a mini sampler for vocals, stabs, or breaks, adding a touch of creativity to any DJ set.



3. VOXOA TUNEBOX database builder software

VOXOA TUNEBOX software makes reading and searching files much quicker and easier. The VOXOA TUNEBOX scans all of music files in your USB mass storage devices and then creates a database file by which you can quickly locate files in your music library.



4. Relay Play

Music can be played alternately from two decks using Relay play. The players can provide automatic, sequential playing tracks one after another from both decks.



5. DSP Digital Sound Effects

The S60 supplies the DJ with four different types of on-board DSP digital effects, including Echo, Flanger, Filter and Pan, to enhance creativity and performance. Also, effect parameters Time and Depth can be adjusted independently via the jog wheel.



6. Rich Input ports + Sound Card Output

S60 is a standard mixer with two line/phono inputs and two microphone inputs. S60 includes a sound card with balanced and unbalanced output, so DJs can simply connect to the speaker or headphones and start the fun of mixing and DJing.



7. Tempo Control and Range

A 100mm linear high-precision slider gives DJs total control and ensures that the tempo adjustment is easy and accurate. The range of tempo +/- 6%, +/-10%, +/-16% and +/-100% can be assigned to the Tempo Control slider.



8. Two Decks Share the Same USB device

Two decks can share a single external USB mass storage device from just one USB device. DJs don't need to have several USB storage devices for different players and can easily manage their music resources from one storage device.

Other Functions

- Automatic and manual tap beat counter
- Cue Play function can back to cue and play instantly
- Relay play
- Single and Continuous play modes
- Auto cue function cues track to start of music
- Seamless loop/reloop function
- High quality 100 mm long pitch fader
- Two Touch sensitive multifunctional jog wheel for search, pitch bend and effects adjustment
- 3 modes for jog wheel: Normal CDJ, Scratch, Cue Scratch
- 2 Large extra bright dot-matrix VFD display
- Three-band EQ with Full output kill for each channel
- Fader start
- 2 MIC with level control, tone adjust and talkover
- Replaceable Crossfader with 3 curve switch
- Headphone with level control and cue mixing
- Booth out with level

*All specifications and appearances are subject to change without notice. VOXOA reserves the rights to change the design for products improvement.

VOXOA Co., LTD

Suite 1801-5,18/F., Tower 2, China Hong Kong City,
 33 Canton Road, Tsim Sha Tsui, Kowloon, Hong Kong
 http://www.voxoa-pro.com
 Email: service@voxoa-pro.com

