

# P10 Multimedia Audio Player

- All-in-one Design
- Combines a CD-Player, MP3-player and AM/FM tuner
- Play regular audio CD's as well as MP3 files
- Multi-output Function
- Variable Output with Volume Control
- Variable Output with Automatic Switch



**Specification**

Power: AC100~240V 50/60 Hz  
 Consumption:10WATTS  
 Dimension:482mm(W)x330mm(D)x44mm(H)  
 Weight:3.82 Kg  
 Inputs:Slot-in CD Player , USB port , SD/MMC reader  
 Outputs:Tuner Output X1 , CD/MP3X1 , VariableX1  
 Frequency Response:20Hz – 20KHz  
 Audio Decoder:  
 MPEG1/2/5 Layer 2/3 decoding (8 KHz – 48 KHz)  
 WAV V4,V7,V8,V9(L1, L2) decoding (8 KHz – 48 KHz)



**Features**

**1.All-in-one Design**

P10 is an All-In-One audio source device, it combines a CD-Player, MP3-player and AM/FM tuner into one singlerack space 19" housing.On the front side is a CD slot, an USB slot and a SD/MMC memory card slot provided. This makes it possible to play regular audio CD's as well as MP3 files from either CD's, USB memory sticks or SD/MMC memory cards.



**2.Multi-output Function**

On the rear side of the device are three stereo outputs provided. Two of them are dedicated to the tuner and CD/MP3 function, while the third output is a variable output. Because of the two separate stereo outputs, the tuner and CD/MP3 player can operate simultaneously. This feature can be useful for applications such as Multi-Zone systems where multiple audio sources are required at the same time.



**3.Variable Output with Volume Control**

The variable output has a volume control function, the output level can be adjusted by rotating function selector dial.



**4.Variable Output with Automatic Switch**

The variable output carries the signal from the CD/MP3 player when a track is playing, but when the CD/MP3 has ended, the variable output will automatically switch to tuner function.



\*All specifications and appearances are subject to change without notice. VOXOA reserves the rights to change the design for products improvement.

